



Technical Bulletin

Nortel Business Communications Manager 200 and Business Communications Manager 400

Technical Specifications

Base unit		
Physical dimensions	BCM400	BCM200
Depth	18.3 in.; 46.5 cm	18.3 in.; 46.5 cm
Width	17.5 in.; 44.5 cm	17.5 in.; 44.5 cm
Height	7.1 in.; 18.0 cm	3.5 in.; 9.0 cm
Weight	Std. 35.2 lbs; 15.9 Kg Redundant 46.7 lbs; 21.2 Kg	Std. 24.9 lbs; 11.3 Kg
Components		
	BCM400	BCM200
Media Bay Module Bays	Four	Two
CPU Processor	Intel Celeron 1.2 GHz	Intel Celeron 1.2 GHz
Memory (RAM)	256 MB SDRAM	256 MB SDRAM
Hard Drive	20 GB EIDE	20 GB EIDE
System Status LEDs		
Power status, Hard drive activity, System status, PCI device monitoring (MSC, WAN, NIC 1, NIC 2), Chassis/CPU temperature, Fan activity reset button		
The System Status Monitor Card controls and monitors fans, power supply, chassis temperature and OS status.		
Mounting options		
Rack-mount (standard 19-inch rack); Stand-alone (feet included); Wall-mount (optional wall-mount bracket available separately)		
Power supply specifications		
Standard power supply	Redundant power supply (BCM400 only)	
Auto-sensing	Auto-sensing	
300 Watts	350 Watts	
90/264 VAC	90/264 VAC	
6.0 A/3.0 A	7.0 A/3.5 A	
60/50 Hz	60/50 Hz	

Environmental specifications

Operating temperature	32° to 104°F; 0° to 40°C
Operating humidity	10% to 90% relative humidity, non-condensing
Storage temperature	-67° to 158°F; -55° to 70°C
Storage humidity	Up to 95% relative humidity

Mechanical requirements

NEBS (GR-63-CORE) compliant for Transportation and Operational Vibration per IEC 68-2-27, Package Drop Shock resistance per ISTA 1A Transportation Bounce to IEC 68-2-55 and Unpackaged Drop to ISTA Project 1A

Regulatory compliance

Electromagnetic emissions

Radiated Air	Australia AS3548 Class A North America CISPR22 Class A United Kingdom EN55022 Class A
Conducted Power Leads	Australia AS3548 Class A North America CISPR22 Class A United Kingdom EN55022 Class A

Immunity (Narrow band RF interference)

Radiated	North America customer driven (based on EN 61000-4-3) United Kingdom/International EN55024 : 1998
Conducted	North America customer driven (Based on EN 61000-4-6) United Kingdom/International EN55024 : 1998

Immunity to electrostatic discharge

Indirect	No functional impairment up to +/- 8 kV
Direct	Mated I/O ports and connectors, No damage up to +/- 4 kV Mated connector and cords, No functional impairment up to +/- 8 kV, No damage up to +/- 15 kV

Network protection

- Australia TS038/31/03/04/01
- EU CTR12/13/3/4/21
- North America/CALA FCC Part 68, CS 03 Issue 8

Safety and surge/transient

- Australia TS038/31/02/03/04, ACA TS001, AS/NZS 3260
- NA/CALA/APAC IEC/EN 60950-1 (including all group and national deviations) and CSA C22.2 No. 60950-1, UL60950-1
- EU CTR12/13/3/4/21, EN 60950 (with national deviations)
- United Kingdom EN60950

Telephony components

Media Services Card (BCM-MSC)

- One 8-pin modular jack (RJ-45) connection for Expansion Chassis (Only on BCM400 not BCM200)
- Four 3.5 mm (1/8 inch) standard miniature stereo (3-conductor) Safety Extra Low
- Voltage (SELV) jacks for auxiliary ringer, page relay, page output and music on hold
- Auxiliary ringer switch capacity of 50mA (non-inductive) at 40 V (maximum)
- Page Relay switch capacity of 50mA (non-inductive) at 40 V (maximum)
- Page Output 600 ohms impedance
- Music on hold mono input
- Media Services Processor Expansion Card slots
 - BCM400—four slots, two equipped
 - BCM200—two slots, one equipped
- Supports maximum of 8 DS-30s. Allows 2/6 and 3/5 IP/TDM Splits.

Media Bay Modules features

16 Stn Digital Station Media Bay Module+ (DSM 16+)

- One Amphenol (male) connector (25 pair)
- Individual interfaces are current connector (25-pair); limited to 80 mA
- 16 digital phone ports
- Two LEDs: Power, Status
- Utilizes 1/2 DS-30 (with DIP switch set appropriately)

32 Stn Digital Station Media Bay Module+ (DSM 32+)

- Two Amphenol (male)
- Individual interfaces are current connectors (25 pair); limited to 80 mA
- 32 digital phone ports
- Two LEDs: Power, Status
- Utilizes 1 DS-30 (with DIP switch set appropriately)

8 Stn Analog Station Media Bay Module (GASM 8)

- One Amphenol (male) connector (25 pair)
- Maximum modem connection speed: 28.8 kbps
- 8 analog phone ports
- Loop length 26G 2600 ft, 24G 4000 ft; 22G 6500 ft
- Disconnect Supervision-850 ms. Momentary Disconnect (Open Switch Interval (OSI) as per TIA/EIA 464)
- Message Waiting Indication – NA 120V. 600 ms On and 1000 ms Off. UK reverse polarity
- Analog connectivity support for Poland and Australia
- Calling Line Identification (CLID) Name and Number – NA per Bell 202 standard. UK per SIN 227/224.
- Two LEDs: Power, Status
- Utilizes 1/4 DS-30 (with DIP switch set appropriately)

Digital Trunk Media Bay Module (DTM)

- One 8-pin RJ-45C modular jack
- T1 trunk interface with integrated CSU
- 24 B channels with T1 interface (supports DSX-1 and DS1 interfaces)
- 23 B channels with North American PRI interface
- LEDs: Power, Status, In-service, Loop-back, Test, Receive Alarm, Receive Error, Transmit Alarm, Transmit Error
- 30 digital channels with ETSI PRI Interface
- Utilizes 1 (one) DS-30

Digital Drop and Insert MUX Media Bay Module (DDIM)

- One 8-pin RJ-45C modular jack
- T1 trunk interface with integrated CSU
- 24 B channels with T1 interface (supports DSX-1 and DS1 interfaces)
- LEDs: Power, Status, In-service, Loop-back Test, Receive Alarm, Receive Error, Transmit Alarm, Transmit Error
- LEDs: Transmit, Receive, RTS, CTS, DCD, DSR, TM
- V.35-DB26 miniature connector
- Cables: V.35, BCM WAN, Nortel Routers, DB-60 cable
- Utilizes two DS-30s

Basic Rate Interface Media Bay Module (BRIM S/T)

- Four modular RJ-45 jacks
- Supports four S/T interfaces (8 B-channels)
- T-interface to connect to an NT1 device or an S-interface to connect ISDN terminals
- Supports ETSI and National ISDN BRI
- Two LEDs: Power, Status
- Utilizes 1/3 DS-30

Global Analog Trunk Module (GATM 4)

- One Amphenol (male) connector for analog North American, UK and Australia Standard
- Four loop start CLASS/CMS lines plus one auxiliary port for V.90 modem, fax, analog telephone connection or Power Fail Transfer
- Two LEDs: Power, Status
- Utilizes 1/4 DS-30

Global Analog Trunk Module (GATM 8)

- One Amphenol (male) connector for analog North American, UK and Australia Standard
- Eight loop start CLASS/CMS lines plus one auxiliary port for V.90 modem, fax, analog telephone connection or Power Fail Transfer
- Two LEDs: Power, Status
- Utilizes 1/2 DS-30

Fiber Expansion Media Bay Module (FEM)

- Six fiber ports
- Connects up to six Norstar* fiber-based trunk or station modules
- Two LEDs: Power, Status
- Utilizes 1 DS-30 for each Norstar fiber trunk or station module connected (up to 6)

Global 4X16 Module (4 Caller ID trunks + 16 Station sets, G4x16)

- One Amphenol (male) connector (25 pair) to support four loop start CLASS/CMS lines plus one auxiliary port for V.90 modem, fax, analog telephone connection, or Power Fail Transfer
- One Amphenol (male) connector (25 pair) to support 16 digital phone ports
- Individual Station interfaces are current limited to 80mA
- Two LEDs: Power, Status
- Utilizes 1 1/4 DS-30s

Global 8X16 Module (8 Caller ID trunks + 16 Station Sets, G8X16)

- One Amphenol (male) connector (25 pair) to support eight loop start CLASS/CMS lines plus one auxiliary port for V.90 modem, fax, analog telephone connection or Power Fair Transfer
- One Amphenol (male) connector (25 pair) to support 16 digital phone ports
- Individual Station interfaces are current limited to 80mA
- Two LEDs: Power, Status
- Utilizes 1 1/2 DS-30s

ADID Module (Analog Direct Inward Dial 4-Port or 8-Port, ADID4 and ADID8)

- One Amphenol (male) connector (25 pair) to support four or eight ADID lines
- Two LEDs: Power, Status
- Utilizes 1/4 DS-30 (ADID4) or 1/2 DS-30 (ADID8)
- Currently North America DID standard

Data networking components

Embedded v.92 Modem

- For Dial Backup or Remote Admin
- V.92 56 kbps ITU standard
- V.34 33.6 kbps ITU standard
- RJ-11 connector
- V.42/MNP 2-4 error control
- V.42/MNP 5 data compression
- Capable of receiving data at 56 kbps and sending data at 31.2 kbps

10/100 Ethernet LAN interface

- 10/100BASE-T Ethernet ports (on board the mainboard)
- Supports IEEE 802.3 Ethernet frame format
- Uses Carrier Sense Multiple Access with Collision Detection (CSMA/CD)
- 100BASE-TX with RJ-45 connector
- 10/100 Auto-sensing
- Full-duplex support
- PPPoE (enabled using keycode)

WAN interface

Two port PCI card (field installable)

- Each port can be independently configured to Frame Relay or PPP
- STAC compression support
- One serial sync port (V.35) and one T1 port with integrated CSU and DSU connectivity – N.A. only
- Two serial ports (V.35)
- Two serial ports (V.35 and X.21) – EMEA only
- Frame Relay or PPP Fragmentation
- RTP Header Compression

ISDN via MBMs

- Up to 16 ISDN B-channels
- (PRI or BRI) (optional)
- Dial on demand, Persistent or WAN Backup
- MLPPP

Expansion Cabinet (BCM400 and BCM1000 only)

Connections

- Six Media Bay Module slots
- An 8-pin modular DS256 connector for the interface to the Business Communications Manager base unit (5 meter cable)

Standard Expansion Cabinet

Depth 18.3 in.; 46.5 cm

Width 17.5 in.; 44.5 cm

Height 5.4 in.; 13.6 cm

Expansion Cabinet with no Media Bay Modules 24.75 lb.; 11.25 kg

Expansion Cabinet with six Media Bay Modules 39 lb.; 17.75 kg

Redundant Expansion Cabinet (redundant power supply and fans)

Depth 20 in.; 53.8 cm

Width 17.6 in.; 44.6 cm

Height 5.4 in.; 13.6 cm

Expansion Cabinet with no Media Bay Modules 31.9 lb.; 14.5 kg

Expansion Cabinet with 6 Media Bay Modules 46.2 lb.; 21 kg

Power requirements

Standard Power Supply

Auto-sensing

300 Watts

90/264 VAC

6.0 A/3.0 A

60/50 Hz

Redundant Power Supply

Auto-sensing

350 Watts

90/264 VAC

7.0 A/3.5 A

60/50 Hz

Environmental ranges

Operating temperature 32° to 104°F; 0° to 40°C

Operating humidity 10% to 90% relative humidity, non-condensing

Storage temperature -67° to 158°F; -55° to 70°C

Storage humidity Up to 95% relative humidity

Mounting options

Rack-mount (standard 19-inch rack); Stand-alone (feet included); Wall-mount (optional wall-mount bracket available separately)

Telephones and Adapters

Station Sets

Business Series

North America	Dimensions (Inches)	Loop Length (26G)	With SAPS sets
T7100	8.1D x 7Wx3.5H	1,000 ft.	2,600 ft.
T7208	8.1D x 7.7Wx3.5H	1,000 ft.	2,600 ft.
T7316E	8.1D x 10.3Wx3.5H	1,000 ft.	2,600 ft.
T24 KIM	7.7D x 3.6Wx3.4H	Connects to T7316E	
NACU	12.5 x 12Wx2H	1,000 ft.	2,600 ft.

IP Stations

- Nortel IP Phone 1120E
- Nortel IP Phone 1140E
- Nortel IP Phone 2007
- Nortel IP Phone 2004
- Nortel IP Phone 2002
- Nortel IP Phone 2001
- Nortel IP Phone 2033
- Nortel IP Softphone 2050 (PC or Laptop)

T24 Kim—requires T7316E

T24 EKIM (Enhanced KIM – used as CAP) – max. 12 positions per system; max 4 EKIMs per position

T24 OKIM (Ordinary KIM – used for answer/DSS/BLF) – unlimited per system; max 4 OKIMs without power supply per position; max 9 OKIMs with power supply per position

WLAN

- WLAN Handset 2210
- WLAN Handset 2211
- WLAN Handset 2212
- WLAN IP Telephony Manager 2245
- WLAN Applications Gateway 2246
- Nortel Mobile Voice Client 2050

Digital Mobility

- Digital Mobility Controller
- Digital Mobility Basestation
- Digital Mobility Repeater
- Digital Mobility Handsets 7420, 743x, 744x, 413x, 414x

Mobility – Cordless

T7406: 3 handsets per basestation, 2 basestations per system

Accessories

BST Doorphone

Norstar Audio Conferencing Unit (NACU)

Station Auxiliary Power Supply (SAPS)

ATA-2 Analog Terminal Adapter (separate models for NA, Europe and Australia)



NN111380-022607

